Operation Instructions

M-254 Infrared Motion & Presence Safety Sensor





1 Safety Instructions



Thank your for your purchasing, please refer to the following details before using:

2 Product Overview







- Bottom Cover
- 2 Top Cover
- 3 Wire holes
- 4 Screw holes x 3

9 Led Indicator


- 5 Dip Switch6 6-pin lineWidth adjustment of inner 2 lines
- 7 Deepth adjustment of inner 2 lines
 - Width adjustment of outer 2 lines


3 Characteristics


8 Deepth adjustment of outer 2 lines

- This sensor integrates the motion and safety function by infrared technology, is applied to the automatic door for opening and safety function. Efficient and precise to control the inductive range. Infrared anti-pinch function adopt background self-learning function, auto adapt to various occassions intelligently.
- Automatic and real-time accurate compensation for time drift of the background, self-correction due to changes in various external factors (such as: vibration, deformation, gradual shift, light and dark, and sunlight, etc.) to ensure the long-term and reliable operation of the detector.


4 Installation









5 Wiring Diagram & Dip Switch Setting




Time of background updated	15S	1 M	1 2 30M	
Motion relay	t 3 NO		NC	
Presence relay	t 4 NO		U 4 NC	
Sensibility of motion	t 5 High		Low	
Sensibility of presence	f e High		Low	


6 Infrared Activation Sensing Field





Width adjustment of the inner or outer 2 lines:





Note: If it is installed on the hallway, and the distance between the sensor and the wall are less than 1.3 meters, please adjust the width of the smaller, to avoid being restrict by wall.

7 Parameter

	Power input:	AC/DC 12~24V(±10%)	Quantity of ray:	1 line for presence, 4 emits, 16 spots
	Cable length:	2.5m		3 lines for motion, 12 emits, 48 spots
	Signal output:	Relay, 1 for motion, 1 for presence	Self-learning time:	10s
ı	Max installation height:	3000mm	Operation indicate:	Standby by green led, motion by yellow led,
ı	Static current:	30mA(DC12V)		Presence by red led
	Action current:	110mA(DC12V)	Temperature:	-40°C~60°C
	Cover:	ABS	Detection range:	1600(W)×800(D)mm
	Ray type:	Infrared modulated light	Respond:	≤100ms
	Ray source:	Infrared 940nm	Dimension:	229(L)×67(W)×41(H)mm
_				

8 Packing list

NO	Parts	PSC	Remark
1	Sensor	1	
2	Instructions	1	
3	Screws bag	1	
4	Wiring	1	2.5m